



NAUTILUS
USER GUIDE

TABLE OF CONTENTS

INTRODUCTION	2
WARNINGS	3
LITHIUM BATTERIES	3
ROTATING IMPELLER(S)	4
WATER INTRUSION	4
PARTS	4
SPECIFICATIONS	5
MOTOR	5
BATTERY	5
GENERAL	5
GETTING STARTED	5
CHARGING THE BATTERY	5
REPLACING THE BATTERY	5,6
TANK MOUNTING	7
TRIGGER	7
MAINTENANCE	8
FAILURE MODE	8
AFTER USE	8
BATTERY O-RINGS	8
DEALER MAINT. SCHEDULE	9
TROUBLE SHOOTING	9
TECHNICAL SPECIFICATIONS	10
WARRANTY	11
CONTACT	12

INTRODUCTION

Congratulations on your purchase of your new Indigo Industries NAUTILUS^{XP} Recreational Dive Propulsion Vehicle (DPV). The NAUTILUS^{XP} is the worlds first tank mount recreational DPV. It is not intended to be a ride, but rather a tool to assist you in improving your dives by increasing bottom time through lower exertion, assisting with photography and aiding in ascent/stop control. Properly Used, NAUTILUS^{XP} will provide years of enjoyment. Please note: NAUTILUS^{XP} is not designed to control your dive. Follow all safety rules of diving at all times while diving. Do not dive without proper certification from a suitable training agency and instructor.

WARNINGS

Lithium Batteries

Lithium-ion batteries can explode, catch fire, and/or cause burns if disassembled, punctured, cut, crushed, short-circuited, incinerated, or exposed directly to water, fire, or high temperatures. To ensure optimal safety and performance:

- DO NOT Use only batteries labeled for use with your Indigo Industries product.
Do not use this battery for any other device.
- DO NOT use counterfeit or inferior-quality batteries in Indigo Industries products (see above). Use only Indigo Industries brand batteries purchased from an authorized Indigo Industries Dealer.
- DO NOT place loose batteries assemblies in a receptacle containing metal objects.
- DO NOT store batteries with hazardous or combustible material; store in a cool, dry, ventilated area.
- ALWAYS keep batteries away from children.
- NEVER attempt to recharge an Indigo Industries lithium battery module with any other recharger than the appropriate Indigo Industries charger purchased from an Authorized Dealer.
- In the unlikely event lithium batteries catch fire, DO NOT attempt to put the fire out with water—use a Class D fire extinguisher or other smothering agent.
- Follow applicable laws and regulations for transport, shipping, and disposal of batteries.

For details on recycling lithium, lithium-phosphate, and lithium-ion batteries, please contact a government recycling agency, your waste-disposal service, or visit reputable on-line recycling sources such as www.batteryrecycling.com.

Failure to follow these warnings and/or directions could result in damage to your Indigo Industries battery/batteries and or product.

Rotating Impeller(s)

Never stick any body part or object into the impeller(s). Do not wear loose flowing clothing that may come into contact with rotating impellers.

Do not use NAUTILUS ^{SP} without a cap that controls all flowing hair. Pay particular attention to those near you with long hair.

Water Intrusion

Be sure to check all sealing areas prior to each and every dive. Battery cap O-rings should be checked on every dive for damage and replaced every 10 dives. If water enters any part of the unit, return to an authorized Indigo Industries dealer for inspection. Remove batteries immediately if wet and return them to an Authorized Indigo Industries dealer for review.

Parts

Thruster/DPV Housing

Battery Assemblies

Caps

Battery Chargers

Triggers

GETTING STARTED

Charging the Battery

The NAUTILUS^{XP} utilizes two high-density lithium Ion Phosphate battery modules.

Each module contains a Battery Management System (BMS) that continuously protects against over-temperature, over-charge, over-discharge, and over-current. Sensing of any of these events will immediately shut down the system. The BMS also balances the battery cells on each charge. To ensure the most production from your modules, an initial charge of 4 hours is needed.

- Using the cap tool provided, unscrew the rear caps by inserting the tool into the provided hole and turning the cap counter clockwise. Because there is a large surface and two O-rings, there will be continuous tension on the cap.
- Carefully set the cap aside ensuring that the o-rings stay clear of debris and dirt.
- Disconnect the XT60 connector.
- Repeat on the second tube.
- Plug in the small lead from the batteries into the charger provided. The charger can charge both batteries at the same time.
- While charging, the indicator light on the charger will remain constant red. Once charged, it will change to green. Waiting an additional 30-minutes after green on the initial charge will balance the cells.

Replacing the Battery

- Using tool provided, unscrew the from caps by inserting the tool into the provided hole and turning the cap counter clockwise. Because there is a large surface and two O-rings, there will be continuous tension on the cap.
- Carefully set the cap aside ensuring that the o-rings stay clear of debris and dirt.

Replacing the Battery Cont.

- Disconnect the connector and carefully pull the battery module from the tube.
- Repeat on the second tube.
- Plug in the batteries to the charger provided. The charger can charge both batteries at the same time.
- While charging, the indicator light on the charger will remain constant red. Once charged, it will change to green. Waiting an additional 30-minutes after green on the initial charge will balance the cells.

To replace the batteries, repeat in reverse the removal steps. Hold the wires and plug in the tube to the inside while sliding the battery in. This will avoid pushing the wires into the tube or damaging them. The module nests into the center of the rear cap. If the module doesn't drop completely into the tube, pull it out ½ inch and reposition until the modules are centered. **DO NOT USE FORCE.** The module should sit easily into the tube and front cap.

Inspect the O-rings on each cap for signs of wear. Replace every ten removals regardless of apparent condition. To replace:

- Using an O-ring removal tool hook the inner O-ring and slide it over the outer O-ring and off of the cap. Remove the outer O-ring next. This sequence prevents the inner O-ring from falling into the vacant outer O-ring groove.
- Ensure that there are no foreign objects in the O-ring grooves. Carefully clean with a cotton swab
- Apply Molykoto 111 Grease to the new O-rings and carefully stretch them into their respective grooves beginning with the first or out groove. Next stretch the inner O-ring over the outer O-ring and into its groove.
- Ensure that the O-rings are seated completely in the groove.
- You may now install the end cap.

Tank Mounting

The NAUTILUS^{XP} is designed to mount onto the back of the SCUBA tank. To do so, loop the strap into the buckle forming a loop. Slide the loop and NAUTILUS^{XP} over the tank until the bottom of the NAUTILUS^{XP} is about 1/2 inch from the bottom of the tank. Tighten the strap. NOTE: If the BCD cam strap inter-fears, leave the NAUTILUS^{XP} loose in position. Tighten the BCD and then tighten NAUTILUS^{XP}.

Trigger Warnings

- The trigger is ALWAYS to be used in the left hand. This keeps your right hand free to access your regulator should the need arise.

Forward/Reverse

NAUTILUS^{XP} features both forward and reverse control. The trigger is a rocker design. When the front (away from the connecting wire) is depressed, NAUTILUS^{XP} will drive forward. When toggled toward the wire connection or back, it will reverse.

Sleep Mode

To ensure that maximum battery is available and to protect against accidentally pushing the trigger in travel, the NAUTILUS^{XP} goes into a sleep mode when not toggled for three minutes.

TO TAKE OUT OF SLEEP MODE TOGGLE THE FOLLOWING SEQUENCE

**REVERSE
FORWARD
FORWARD**

A TONE WILL OCCUR UPON AWAKENING.

Failure Mode

- A safety feature designed into the device protects against the unlikely event that the motor stay in the on position. In this instance pushing the trigger the opposite direction will shut down the system.

MAINTENANCE

After Use

- Rinse with fresh water after every use.
- Disconnect batteries
- Wipe down the finish and free any small debris from the impeller.
CAUTION: Do not insert any object, including fingers, into the impeller housing unless both batteries have been unplugged. Verify this is complete by depressing the trigger while out of sleep mode. Only clear this when no power is connected.

Battery O-Rings

- Replace the battery O-rings at the back of NAUTILUS^{XP} after every ten cap removals or if O-rings become damaged in any way. Follow instructions on page 6.
- Ensure that there is proper lubrication before every use.

Dealer Maintenance Schedule

- An annual inspection by an Authorized Indigo Industries Pro Shop is required. Failure to have an annual inspection will void the owners warranty.
- Annual replacement of front cap O-rings and electrical box O-rings is required. These components, as well as an annual inspection, are to be performed only by an Authorized Indigo Industries Pro Shop.

Troubleshooting

Batteries won't charge.

- Ensure the charger cord is plugged into both a power source and the charger itself
- Ensure the charger is properly connected to the battery connector.
- Review charger. Is the light coming on in green (indication of full charge).
- Review battery connector for damage. If found, return battery module and charger to an Authorized Indigo Industries dealer for inspection.

NAUTILUS^{XP} won't turn on.

- Check to ensure the unit is not in sleep mode.
- Ensure the batteries are properly charged.
- Ensure batteries are properly installed and plugged into the unit.
- Return the unit to an Authorized Indigo Industries Pro Shop for review.

NAUTILUS^{XP} is charged and awake but the motor wont go in one or either direction.

- Unplug BOTH batteries, wait 30 seconds, and plug them both back in. Toggle the trigger of sleep mode.
- If there is still no response, return the unit to an Authorized Indigo Industries Pro Shop for review.

Technical Specifications

SPECS	NAUTILUS ^{XP}
DESIGN	Indigo propriety design <i>patent pending</i>
MOTOR TYPE	Brushless PM
ENVIRONMENTAL	Operates at extreme pressure and depth <small>—APPROVED FOR DEPTH 120 FT</small>
BEARINGS	Non-corrosive
VOLTAGE RANGE	6-20 Volts
MAX CURRENT	22 amps
MAX POWER	350 watts
SPEED RANGE	300-3800 RPM
FORWARD THRUST	12 #
NOMINAL VOLTAGE	16 volts
BATTERY PACK CAPACITY	15 AHR and 240 WHR
LITHIUM CELL TYPE	26650 — <small>APPROVED BY TSA FOR FLIGHT WHEN THE TWO CELLS ARE IN SEPARATE BAGS</small>
CELL CONFIGURATION	556P
TYPICAL RUN TIME	40 minutes
COLOR OPTIONS	Lightning Blue and Midnight Black

Warranty

Indigo Industries Inc. warrants Indigo Industries products to the original retail purchaser to be free of defects in material and workmanship for as long as the original purchaser owns the product. Failure to complete regular maintenance will void this warranty. All other conditions of the standard Indigo Industries Inc. product warranty apply.

Standard Indigo Industries Warranty

Indigo Industries warrants all Indigo product for the period of two years from date of purchase. This warranty does not apply to commercially used product.

Indigo Industries will repair or replace any warranted component or replacement part that is defective in materials or workmanship. Replacement or repair of Indigo Industries product is its only obligation under this warranty.

Indigo Industries is not liable for loss of or expenses and/or that are incidental, consequential or indirect.

Warranty is fully void if product is purchased by the consumer from an outlet that is not an Authorized Indigo Industries dealer. This warranty does not cover or include product finish, improperly installed or applied products, improperly maintained products, or damage due to abuse or neglect.

Contact

Indigo Industries
4626 North 300 West #150
Provo, UT 84604

Phone: 385-374-0444

Connect With Us Online:

Website: www.Indigo-Industries.com

Facebook Page: www.facebook.com/indigoindustriesscuba

Twitter: [/indigoindustrie](https://twitter.com/indigoindustrie)

Instagram: [@indigoindustries](https://www.instagram.com/indigoindustries)



INDIGO
INDUSTRIES

INDIGO-INDUSTRIES.COM